

Products

- HiFi
- Home Theatre
- Systems
- Network Products
- KI-Pearl
- Accessories
- Previous Models



> [Home](#) > [Products](#) > [Home Theatre](#) > [AV-Amplifier](#) > [NR1601](#)

NR1601



- Overview
- Features
- Reviews
- Specifications
- Downloads

Specifications

MULTICHANNEL SURROUND

THX Ultra II / Select II	-
THX Surround EX	-
DTS HD Master / DTS 5.1 / DTS ES / DTS 96/24	o / o / o / o
Dolby Digital Plus / Dolby TrueHD / Dolby Digital EX / DPL IIz	o / o / o / o
Audyssey DSX	-
Circle Surround II / Neural Surround	o / o
Virtual Surround / Multichannel Stereo	o / o
HT-EQ / Re-EQ	o / -
Dolby Headphone	o
Compressed audio Enhancer: MDAX / MDAX2	- / o

SOUND ENHANCEMENTS

Current Feedback Topology	-
Hyper Dynamic Amplifier Modules (HDAM)	-
Pure Direct	o
Power Transformer: Toroidal / EI	- / o
High Grade Audio Components	-
Chassis: Copper plated / Metal	- / o

NETWORK

DLNA certified	-
UPnP Certified	-
Network Audio: MP3 / WAV / AAC / FLAC / WMA	-
Network static video (JPEG)	-
Network Video	-
Integrated webserver	-
Internet Radio: direct / external media player	-
vTuner / Napster	-
WiFi: integrated / external access point	-
Ethernet	-
IP Control	-

OTHERS

Bluetooth audio via RX101	optional
Auto speaker setup by microphone	Audyssey MultEQ
Audyssey Dynamic EQ / Dynamic Volume	o / o
Video conversion	CVBS > HDMI; Comp > HDMI
Interlace / progressive conversion	o (576i -> 576p)
Analogue to HDMI scaling	o (576p)
HDMI to HDMI scaling	-
Videoprocessing	o
Picture adjust / Noise reduction	- / -
HDMI path though on stand-by	o
Deep Color pass through	o
3D video pass through	o
Audio Return Channel	o
CEC	o
T.B.C. - time base correction	-
Front panel cursor control	o
On Screen Display: GUI / OSD	- / o
Variable cross over	10
Lip sync control	o

Multiroom zones	-
Front Flap	-
Discrete RC coding (Main- / Multiroom)	o / -

INPUTS/OUTPUTS

Composite In / Out	3 / 1
S-Video In / Out	- / -
Component In / Out	3 / 1
HDMI In / Out (version x.x)	4 / 1 (1.4a)
Multi-Room Video Out: Video / Component	- / -
Analogue In / Out	6 / 0
Balanced In / Out	-
Phono (MM) In	-
Digital Optical In / Out	2 / 0
Digital Coaxial In / Out	1 / 0
Multi-Room Out: analog / digital	- / -
Multichannel Pre Out / Main In	o (0.1) / -
Subwoofer Out	1
7.1 multichannel input	-
M-Xport for RX101	o
Speaker Terminal: Gold plated screw / regular screw	- / o
Number of terminals	9
Speaker A / B	o
Height speaker terminal	Speaker B or Height
Bi-amp drive (5.1 ch setting) / Speaker C	o / o
Multi-Room Speaker Terminal	-
Marantz remote bus	o
IR Receiver In / Emitter Out	- / -
IR Flasher In	o
Network: (IP-control / update)	- / -
RS232C (control / update)	- / -
DC Triggers	-
Front Inputs: Audio / Composite / Digital (Opt) / HDMI /	o / o / o / o

USB

o / - / - / - / o

USB Audio / Made for iPod / Works with iPhone

o / o / o

Specifications

Power Output (8 / 6 ohm, 20 Hz - 20 kHz, 0.08%)

50 W

70% Guarantee

-

Audio Signal to Noise Ratio

98 dB

FM Tuner

o

GENERAL

Available colors: Gold / Silver / Black / Silver-Gold

- / - / o / o

Metal Front Panel

o

System Remote Control

RC010SR

Pre-programmed / Learnable / LCD Display

o / o / -

Power Consumption in W

250

Standby Consumption in W

0.2

Detachable Power Cable

o

Maximum Dimensions (W x D x H) in mm

440 x 367 x 105

Weight in kg

9.0

Options

- [FAQ](#)
- Compare to:

Associated Products

UD5005