

- [HiFi](#)
- [Home Theatre](#)
- [Systems](#)
- [Network Products](#)
- [KI-Pearl](#)
- [Accessories](#)
- [Previous Models](#)



[> Home](#) > [Products](#) > [Network Products](#) > [AV Receiver](#) > [AV7005](#)

AV7005



- [Overview](#)

- Features
- Reviews
- Specifications
- Downloads

Specifications

MULTICHANNEL SURROUND

THX Ultra II / Select II	- / -
THX Surround EX	-
DTS HD Master / DTS 5.1 / DTS ES / DTS 96/24	o / o / o / o
Dolby Digital Plus / Dolby TrueHD / Dolby Digital EX / DPL IIz	o / o / o / o
Audyssey DSX	o
Circle Surround II / Neural Surround	o / o
Virtual Surround / Multichannel Stereo	o / o
HT-EQ / Re-EQ	o / -
Dolby Headphone	o
Compressed audio Enhancer: MDAX / MDAX2	- / o

SOUND ENHANCEMENTS

Current Feedback Topology	o
Hyper Dynamic Amplifier Modules (HDAM)	o
Pure Direct	o
Power Transformer: Toroidal / EI	- / o
High Grade Audio Components	o
Chassis: Copper plated / Metal	- / o

NETWORK

DLNA certified	o (v1.5)
UPnP Certified	o

Network Audio: MP3 / WAV / AAC / FLAC / WMA	o / o / o / o / o
Network static video (JPEG)	o
Network Video	-
Integrated webserver	-
Internet Radio: direct / external media player	o / o
vTuner / Napster	o / o
WiFi: integrated / external access point	- / o
Ethernet	o
IP Control	o

OTHERS

Bluetooth audio via RX101	optional
Auto speaker setup by microphone	Audyssey MultEQ XT
Audyssey Dynamic EQ / Dynamic Volume	o / o
Video conversion	CVBS > Comp > HDMI
Interlace / progressive conversion	o
Analogue to HDMI scaling	> 1080p
HDMI to HDMI scaling	o
Videoprocessing	Anchor Bay (ABT2015)
Picture adjust / Noise reduction	o / o
HDMI path though on stand-by	o
Deep Color pass through	o
3D video pass through	o
Audio Return Channel	o
CEC	o
T.B.C. - time base correction	-
Front panel cursor control	o
On Screen Display: GUI / OSD	o / -
Variable cross over	10
Lip sync control	o
Multiroom zones	2
Front Flap	o
Discrete RC coding (Main- / Multiroom)	o / o

INPUTS/OUTPUTS

Composite In / Out	5 / 3
S-Video In / Out	-
Component In / Out	4 / 2
HDMI In / Out (version x.x)	6 / 2 (1.4a)
Multi-Room Video Out: Video / Component	o / o
Analogue In / Out	8 / 2
Balanced In / Out	- / 7.2
Phono (MM) In	o
Digital Optical In / Out	3 / 1
Digital Coaxial In / Out	2 / 0
Multi-Room Out: analog / digital	2 / -
Multichannel Pre Out / Main In	o (11.2ch) / -
Subwoofer Out	o
7.1 multichannel input	o
M-Xport for RX101	o
Speaker Terminal: Gold plated screw / regular screw	- / -
Number of terminals	-
Speaker A / B	o(pre out)
Height speaker terminal	o(pre out)
Bi-amp drive (5.1 ch setting) / Speaker C	o / o
Multi-Room Speaker Terminal	-
Marantz remote bus	o
IR Receiver In / Emitter Out	- / -
IR Flasher In	1
Network: (IP-control / update)	o / o
RS232C (control / update)	o
DC Triggers	2
Front Inputs: Audio / Composite / Digital (Opt) / HDMI / USB	o / o / o / o / o
USB Audio / Made for iPod / Works with iPhone	o / o / o

Specifications


Power Output (8 / 6 ohm, 20 Hz - 20 kHz, 0.08%)	-
70% Guarantee	-
Audio Signal to Noise Ratio	102 dB
FM Tuner	o

GENERAL

Available colors: Gold / Silver / Black / Silver-Gold	- / - / o / -
Metal Front Panel	o
System Remote Control	RC011SR
Pre-programmed / Learnable / LCD Display	o / o / o
Power Consumption in W	85
Standby Consumption in W	0.2
Detachable Power Cable	o
Maximum Dimensions (W x D x H) in mm	440 x 395 x 187
Weight in kg	11.0

Options

- [FAQ](#)
- Compare to:



Associated Products

UD8004
Universal HD Player



MM7055